

LA-2050/2025

Stand-alone Logic Analyzer and Data Logger /Provide the best measurement solution/

Introduction

The LA-20 Series helps minimize users' project risk by providing the most reliable, accurate data capture and a complete view of system behavior. These products are ideally suited for users on hardware/software debugging, parametric, mixed signal testing, and complex debugging. Moreover, their compact size and ability to connect with a PC for analysis and data logging makes them an ideal solution at remote sites.

Features

Logic Analyzer

- External (synchronous) and internal (asynchronous) capture : Offer a more convenient environment for engineers.
- Provide three sets of searching data functions and six cursor marks. The timing of each trigger point can be shown by the cursor mark.
- Binary code and hexadecimal List mode (State) display.
- Able to save measuring data and waveform results in stand-alone mode.
- Offer I2C, SPI, UART and CAN signal decoding function on PC.
- Provide various signal trigger and capture : Total of four kinds of trigger modes including Pattern/Edge/AND/OR.
- Pre-trigger, post-trigger, 3 level trigger, and continued-trigger functions allow users to operate easily.
- Bus analysis and glitch capture functions: 2M Bytes~4M Bytes long memory depth ; each CH memory depth is up to 512Kbits~1Mbits.
- The adjustable sample rate size can be set by users, which avoids long capturing time.
- Provide "Trigger Counter" and "Pulse Wide Trigger" function.
- High-speed Zoom In / Zoom Out techniques.
- Smart software provides text file for saving the Binary Code of waveform results.
- Compact, portable for engineers to perform debugging.
- 5.6 inch TFT color LCD display.
- USB 2.0 interface for PC link function, which can connect with PC for user to save, analyze, view and printout.



Standard Accessories

Main unitx1
Data podx4
Lead set.....x4
Testing probe (testing hook)
.....x36
AC power cordx1
CD.....x1
(Driver and user manual are included)
USB cable.....x1

Specification

Model	LA-2025	LA-2050
Timing Analysis	250MHz	500MHz
State Analysis	200MHz	200MHz
Bandwidth	200MHz	200MHz
Channels	32CH	32CH
RAM Size	2M Bytes	4M Bytes
Storage Depth per Channel	512K bits x 32CH	1M bits x 32CH
Maximum Input Voltage	±15V	±15V
Threshold Range	-4V~+4V	-4V~+4V
Data Skew (Channel to Channel)	4ns typical (±4ns Max)	2ns typical (±2ns Max)
Trigger Condition	Pattern / Edge / AND / OR	Pattern / Edge / AND / OR
Trigger Counter	1~255	1~255
Pulse Width Trigger	YES	YES
Glitch Capture	4ns	2ns
Communication	USB 2.0	USB 2.0
Power Source	110V AC~240V AC	110V AC~240V AC
Frequency Range	50~60Hz	50~60Hz
Power Consumption	18W (20W Max)	18W (20W Max)
Operating Temperature	0℃~45℃	0℃~45℃
Dimension	31cm x 15cm x 9cm	31cm x 15cm x 9cm
Weight	3.8Kg	3.8Kg

PC System Requirement

Operating System	Windows 98/2000/XP/Vista/32
------------------	-----------------------------

Data Logger

- Provide friendly software, no matter what program language, just key in the timing, trigger condition and logic level etc, then start the data acquisition.
- Use binary for logging the code.